

Resonant mode coupling approximation for calculation of optical spectra of photonic crystal slabs

Dmitrii A. Gromyko*

*Skolkovo Institute of Science and Technology, Nobel Street 3, 121205 Moscow, Russia and
A. M. Prokhorov General Physics Institute, RAS, Vavilova 38, Moscow, Russia*

Sergey A. Dyakov

Skolkovo Institute of Science and Technology, Nobel Street 3, 121205 Moscow, Russia

Sergei G. Tikhodeev

*A. M. Prokhorov General Physics Institute, RAS, Vavilova 38, Moscow, Russia and
Faculty of Physics, Lomonosov Moscow State University, 119991 Moscow, Russia*

Nikolay A. Gippius

Skolkovo Institute of Science and Technology, Nobel Street 3, 121205 Moscow, Russia

This article represents the development of the resonant mode coupling approximation method for determining optical spectra of a stack of two photonic crystal slabs. This method is based on the derivation of the input and output resonant vectors in each slab in terms of the Fourier modal method in the scattering matrix form. We show that using the resonant mode approximation of the scattering matrices of the upper and lower slabs one can construct the total scattering matrix of the stack. We demonstrate that the developed procedure dramatically decreases the computation time without sufficient loss of accuracy. We believe that the proposed technique can be a powerful tool for the fast solving of inverse scattering problems using stochastic optimization methods such as genetic algorithms or machine learning.

I. INTRODUCTION

The development of methods for fabricating nanostructures in the last three decades has led to the emergence of many theoretical tools for the simulation of their optical properties. A great variety of theoretical methods makes it possible to comprehensively study the optical resonances of the entire system and its parts, revealing the contribution of each structural element to the resulting optical response before proceeding with their manufacture [1, 2]. In the engineering of photonic structures and devices, we always deal with photonic modes. By changing the geometry and composition of a structure, we tune the modes' localization, spectral position, and decay time and make them hybridize [3–7]. Due to the great opportunities given by fabrication methods, one can vary many geometrical parameters in wide ranges to achieve the desired optical response, which can take much time to perform. On the other side, in many practically important cases, the structure of interest consists of several parts or subsystems whose optical properties are already known. With this regard, one can consider, for example, a stack of two photonic crystal slabs like in Ref. 8, 9. In these works, it has been demonstrated that one can determine the resonant frequencies of the stack using a resonant mode coupling method based on the resonant modes [10–13] of the photonic crystal slabs found within the formalism of the Fourier modal method [10, 14] also

known as rigorous coupled-wave analysis (RCWA) [15]. It allows fast and efficient variation of the stack's geometrical parameters, for instance, the lateral shifts of the slabs or their thicknesses. For other various applications of the resonant or quasinormal modes concept we suggest to explore Ref. [16].

In this article, we will present a further development of the resonant mode coupling method for the calculation of the stack's optical spectra based on the knowledge of the upper and lower photonic crystal slabs' eigenmodes. We will show that once we know all the resonant energies and the input and output resonant vectors, we can immediately construct a resonant approximation for the scattering matrix of the whole system for any given lateral shift between the subsystems. After that, we will consider a numerical example and compare the approximate reflection spectra of the stack with the results of calculations made by the standard Fourier modal method.

II. COUPLED RESONANCES EXCITED BY AN EXTERNAL PLANE WAVE

By definition, a scattering matrix is the matrix function that provides a relation between the incoming and outgoing electromagnetic waves. According to [17], any scattering matrix can be presented using the resonant approximation:

$$\begin{pmatrix} |d_2\rangle \\ |u_1\rangle \end{pmatrix} = \left[\tilde{S} + \sum_{n=1}^N |O_n\rangle \frac{1}{\omega - \omega_n} \langle I_n| \right] \begin{pmatrix} |d_1\rangle \\ |u_2\rangle \end{pmatrix}. \quad (1)$$

* e-mail: Dmitrii.Gromyko@skoltech.ru

Here $|d, u\rangle$ are the vectors consisting of the complex amplitudes of the electromagnetic waves propagating downwards and upwards respectively. Their subscript indices 1 and 2 indicate that these amplitudes are calculated infinitesimally above the upper boundary or below the lower boundary respectively. Matrix $\tilde{S}$ is a slowly varying matrix function of energy, which we call a background scattering matrix. All the sharp features of the optical spectrum are described by the resonant terms that are first order poles ω_n with residuals $|O_n\rangle \langle I_n|$. We refer to the vectors $|O_n\rangle$ and $\langle I_n|$ as output and input resonant vectors.

In order to derive expressions for the input and output resonant vectors of the whole system, we consider a resonant approximation for the scattering matrices of two subsystems A and B:

$$\begin{pmatrix} |d_2\rangle \\ |u_1\rangle \end{pmatrix} = \left[\begin{pmatrix} \tilde{S}_{dd}^a & \tilde{S}_{du}^a \\ \tilde{S}_{ud}^a & \tilde{S}_{uu}^a \end{pmatrix} + \sum_{n=1}^N |O_n^a\rangle \frac{1}{\omega - \omega_n^a} \langle I_n^a| \right] \begin{pmatrix} |d_1\rangle \\ |u_2\rangle \end{pmatrix},$$

$$\begin{pmatrix} |d_3\rangle \\ |u_2\rangle \end{pmatrix} = \left[\begin{pmatrix} \tilde{S}_{dd}^b & \tilde{S}_{du}^b \\ \tilde{S}_{ud}^b & \tilde{S}_{uu}^b \end{pmatrix} + \sum_{n=1}^M |O_n^b\rangle \frac{1}{\omega - \omega_n^b} \langle I_n^b| \right] \begin{pmatrix} |d_2\rangle \\ |u_3\rangle \end{pmatrix}. \quad (2)$$

Here subscript indices 1, 2, and 3 correspond to the waves propagating above the structure A, between structures A and B, and below structure B respectively.

A resonant mode is a non-trivial solution of the Maxwell's equations with no source [13, 17, 18]. Following this definition, we assume that there is no incoming waves in the system, i.e. $|d_1\rangle = 0$, $|u_3\rangle = 0$. We define the coefficients of the resonant excitation as a product of the resonant input vectors and the nonzero incoming wave amplitudes:

$$\begin{aligned} \alpha_n &= \frac{1}{\omega - \omega_n^a} \langle I_{u,n}^a | u_2 \rangle, \\ \beta_n &= \frac{1}{\omega - \omega_n^b} \langle I_{d,n}^b | d_2 \rangle. \end{aligned} \quad (3)$$

Now we can extract vectors $|d_2, u_2\rangle$ by substituting equations (2) into each other:

$$\begin{aligned} |d_2\rangle &= \sum_{n=1}^N \alpha_n |O_{d,n}^a\rangle + \sum_{n=1}^M \beta_n \tilde{S}_{du}^a |O_{u,n}^b\rangle, \\ |u_2\rangle &= \sum_{n=1}^N \alpha_n \tilde{S}_{ud}^b |O_{d,n}^a\rangle + \sum_{n=1}^M \beta_n |O_{u,n}^b\rangle. \end{aligned} \quad (4)$$

Here we use the following definition of the "dressed" resonant output vector, which is a sum of an initial output vector and all its non-resonant reflections:

$$\begin{aligned} |O_{d,n}^a\rangle &= \underbrace{(\mathbb{I} - \tilde{S}_{du}^a \tilde{S}_{ud}^a)^{-1}}_{\mathbb{D}_1} |O_{d,n}^a\rangle, \\ |O_{u,n}^b\rangle &= \underbrace{(\mathbb{I} - \tilde{S}_{ud}^b \tilde{S}_{du}^b)^{-1}}_{\mathbb{D}_2} |O_{u,n}^b\rangle. \end{aligned} \quad (5)$$

Once we derived the expressions for the vectors of the field amplitudes between the subsystems $|d_2, u_2\rangle$, we insert them into the definition of the resonant coefficients (3) and obtain the following system of equations:

$$\begin{aligned} (\omega - \Omega^a) \alpha &= \langle I_u^a | \tilde{S}_{ud}^b | O_d^a \rangle \alpha + \langle I_u^a | O_u^b \rangle \beta, \\ (\omega - \Omega^b) \beta &= \langle I_d^b | O_d^a \rangle \alpha + \langle I_d^b | \tilde{S}_{du}^a | O_u^b \rangle \beta, \end{aligned} \quad (6)$$

where we defined the diagonal matrices of the subsystems' resonant energies $\Omega^{a,b} = \text{diag}\{\omega^{a,b}\}$. It is more convenient to rewrite this system in a form of an eigenproblem with an effective Hamiltonian whose eigenvalues ω_i are the resonant energies of the stacked system and the corresponding eigenvectors are the resonant coefficients:

$$\begin{pmatrix} \langle I_u^a | \tilde{S}_{ud}^b | O_d^a \rangle + \Omega^a & \langle I_u^a | O_u^b \rangle \\ \langle I_d^b | O_d^a \rangle & \langle I_d^b | \tilde{S}_{du}^a | O_u^b \rangle + \Omega^b \end{pmatrix} \begin{pmatrix} \alpha \\ \beta \end{pmatrix} \equiv \underbrace{\begin{pmatrix} H_{aa} & H_{ab} \\ H_{ba} & H_{bb} \end{pmatrix}}_{\equiv H} \begin{pmatrix} \alpha \\ \beta \end{pmatrix} = \omega \begin{pmatrix} \alpha \\ \beta \end{pmatrix}. \quad (7)$$

These coefficients α, β define the partial contributions of each resonance of subsystems A and B into the resonances of the stacked system. For a given resonance of the stacked system with energy ω_i being the i -th eigenvalue of the matrix H in (7) the corresponding output vector appears in the form:

$$\begin{aligned} |d_3^{(i)}\rangle &= \sum_{n=1}^N \alpha_n^{(i)} \tilde{S}_{dd}^b |O_{d,n}^a\rangle + \sum_{n=1}^M \beta_n^{(i)} \tilde{S}_{dd}^b \tilde{S}_{du}^a |O_{u,n}^b\rangle + \sum_{n=1}^M \beta_n^{(i)} |O_{d,n}^b\rangle \\ |u_1^{(i)}\rangle &= \sum_{n=1}^N \alpha_n^{(i)} \tilde{S}_{uu}^a \tilde{S}_{ud}^b |O_{d,n}^a\rangle + \sum_{n=1}^M \beta_n^{(i)} \tilde{S}_{uu}^a |O_{u,n}^b\rangle + \sum_{n=1}^N \alpha_n^{(i)} |O_{u,n}^a\rangle, \end{aligned} \quad (8)$$

$$|Out_i\rangle = \begin{pmatrix} |d_3^{(i)}\rangle \\ |u_1^{(i)}\rangle \end{pmatrix}. \quad (9)$$

The resonant input vectors should be dependent on the type of excitation. For example, this could be an external plane wave or an oscillating current located between the subsystems A and B. For the case of external plane waves we write the resonant approximation in the desired form:

$$\begin{pmatrix} |d_3\rangle \\ |u_1\rangle \end{pmatrix} = \left[\begin{pmatrix} \tilde{S}_{dd} & \tilde{S}_{du} \\ \tilde{S}_{ud} & \tilde{S}_{uu} \end{pmatrix} + \sum_{i=1}^{L=N+M} |Out_i\rangle \frac{1}{\omega - \omega_i} \langle In_i| \right] \begin{pmatrix} |d_1\rangle \\ |u_3\rangle \end{pmatrix}. \quad (10)$$

One should redefine the resonant coefficients, so that they also account for the incoming waves:

$$\begin{aligned} (\omega - \omega_m^a) \alpha_m &= \langle I_{u,m}^a | u_2 \rangle + \langle I_{d,m}^a | d_1 \rangle, \\ (\omega - \omega_m^b) \beta_m &= \langle I_{d,m}^b | d_2 \rangle + \langle I_{u,m}^b | u_3 \rangle. \end{aligned} \quad (11)$$

We once again extract vectors $|d_2, u_2\rangle$ from the equations (2) and obtain the new system that defines the resonant coefficients:

$$\begin{aligned} (\omega - \Omega^a) \alpha &= \langle I_u^a | \tilde{S}_{ud}^b | \mathbf{O}_d^a \rangle \alpha + \langle I_u^a | \mathbf{O}_u^b \rangle \beta + \\ &+ \langle I_d^a | d_1 \rangle + \langle I_u^a | \tilde{S}_{ud}^b \mathbb{D}_1 \tilde{S}_{dd}^a | d_1 \rangle + \langle I_u^a | \mathbb{D}_2 \tilde{S}_{uu}^b | u_3 \rangle, \\ (\omega - \Omega^b) \beta &= \langle I_d^b | \mathbf{O}_d^a \rangle \alpha + \langle I_d^b | \tilde{S}_{du}^a | \mathbf{O}_u^b \rangle \beta + \\ &+ \langle I_d^b | \mathbb{D}_1 \tilde{S}_{dd}^a | d_1 \rangle + \langle I_u^b | u_3 \rangle + \langle I_d^b | \tilde{S}_{du}^a \mathbb{D}_2 \tilde{S}_{uu}^b | u_3 \rangle. \end{aligned} \quad (12)$$

One can rewrite it in the following form so that the connection with the eigenproblem on resonant states of the stacked system (7) would be obvious:

$$\begin{pmatrix} \alpha \\ \beta \end{pmatrix} \omega = \begin{pmatrix} H_{aa} & H_{ab} \\ H_{ba} & H_{bb} \end{pmatrix} \begin{pmatrix} \alpha \\ \beta \end{pmatrix} + \underbrace{\begin{pmatrix} \langle I_u^a | \tilde{S}_{ud}^b \mathbb{D}_1 \tilde{S}_{dd}^a + \langle I_d^a | \tilde{S}_{du}^a \mathbb{D}_2 \tilde{S}_{uu}^b + \langle I_u^b | \end{pmatrix} \begin{pmatrix} |d_1\rangle \\ |u_3\rangle \end{pmatrix}}_{\equiv f} \quad (13)$$

Here f is a total force that excites the resonances of the stacked system.

To solve system of equations (II) one has to find all eigenvalues and eigenvectors in equation (7):

$$HX = XH_d, \quad (14)$$

H_d is a diagonal matrix of the eigenvalues ω_i , X is a square matrix whose columns are the corresponding right eigenvectors $[\alpha^{(i)}, \beta^{(i)}]^T$ of the matrix H . Then there exists only one set of coefficients $A = [\alpha, \beta]^T$ that satisfies equation (II):

$$A = X \frac{1}{\omega - H_d} X^{-1} f. \quad (15)$$

With the given coefficients we solve system (2) with respect to variables $|d_3, u_1\rangle$ and write the output vectors, input vectors, as well as the background matrix of the resonant approximation (10):

$$\begin{aligned} |Out\rangle &= (|Out_1\rangle, |Out_2\rangle, \dots) = \begin{pmatrix} \tilde{S}_{dd}^b | \mathbf{O}_d^a \rangle & \tilde{S}_{dd}^b \tilde{S}_{du}^a | \mathbf{O}_u^b \rangle + |O_d^b\rangle \\ \tilde{S}_{uu}^b \tilde{S}_{ud}^a | \mathbf{O}_d^a \rangle + |O_u^a\rangle & \tilde{S}_{uu}^b | \mathbf{O}_u^b \rangle \end{pmatrix} X, \\ \langle In| &= \begin{pmatrix} \langle In_1| \\ \langle In_2| \\ \vdots \end{pmatrix} = X^{-1} \begin{pmatrix} \langle I_u^a | \tilde{S}_{ud}^b \mathbb{D}_1 \tilde{S}_{dd}^a + \langle I_d^a | \tilde{S}_{du}^a \mathbb{D}_2 \tilde{S}_{uu}^b + \langle I_u^b | \\ \langle I_d^b | \mathbb{D}_1 \tilde{S}_{dd}^a & \langle I_d^b | \tilde{S}_{du}^a \mathbb{D}_2 \tilde{S}_{uu}^b + \langle I_u^b | \end{pmatrix}, \end{aligned} \quad (16)$$

$$\tilde{S} = \begin{pmatrix} \tilde{S}_{dd}^b \mathbb{D}_1 \tilde{S}_{dd}^a & \tilde{S}_{du}^b + \tilde{S}_{dd}^b \tilde{S}_{du}^a \mathbb{D}_2 \tilde{S}_{uu}^b \\ \tilde{S}_{ud}^a + \tilde{S}_{uu}^a \tilde{S}_{ud}^b \mathbb{D}_1 \tilde{S}_{dd}^a & \tilde{S}_{uu}^a \mathbb{D}_2 \tilde{S}_{uu}^b \end{pmatrix} \quad (17)$$

It appears that the resonant mode coupling method is very effective for modelling of the subsystems which can be shifted relatively to each other along the lateral axes x and y . If subsystem B is shifted relative to subsystem A by a distance d_x along the x axis and by a distance d_y along the y axis, then the background matrix and the resonant input and output vectors of structure B should be transformed as:

$$\begin{aligned} \tilde{S}^b &\rightarrow \tilde{S}^{b'} = P^\dagger \tilde{S}^b P, \\ |O_n^b\rangle &\rightarrow |O_n^{b'}\rangle = P^\dagger |O_n^b\rangle, \quad \langle I_n^b| \rightarrow \langle I_n^{b'}| = \langle I_n^b| P, \end{aligned} \quad (18)$$

where P is a shift matrix defined as

$$P = \text{diag}\{\exp(iK_x d_x + iK_y d_y)\}, \quad (19)$$

with $K_{x,y}$ being the x and y projections of the wavevectors for the Fourier harmonics:

$$K_x = k_x + \frac{2\pi}{p_x}, \quad K_y = k_y + \frac{2\pi}{p_y}, \quad (20)$$

where $k_{x,y}$ are the lateral projections of the incoming wave wavevector.

Here it is important to discuss the applicability criteria of the described resonant mode coupling method. The first one follows from the requirement that we can treat the effective Hamiltonian in (7) and (II) as an approximately constant matrix. At the same time, all the background matrices and as well as the Hamiltonian are, in fact, energy-dependent. This is why we require that all the background matrices are weak functions of energy

in the selected energy range $[\omega_{min}, \omega_{max}]$ used in the approximation:

$$\tilde{S}^{a,b}(\omega \in [\omega_{min}, \omega_{max}]) \approx const. \quad (21)$$

One can try to construct a perturbation theory and include linear terms in energy

$$\tilde{S}^{a,b}(\omega) = \tilde{S}_0^{a,b} + \left. \frac{d\tilde{S}^{a,b}}{d\omega} \right|_{\omega=\omega_0} (\omega - \omega_0), \quad (22)$$

but this will mean that all the resonant output and input vectors (16) should be also calculated at the energy of the corresponding resonance. Further complication of the background matrices energy dependences will lead to the necessity to find poles of the nonlinear function $(H(\omega) - \omega)^{-1}$ so that the solution would be determined by equation (II) in the form:

$$\begin{pmatrix} \alpha \\ \beta \end{pmatrix} = (\omega - H(\omega))^{-1} \langle In(\omega) | \begin{pmatrix} |d_1\rangle \\ |u_3\rangle \end{pmatrix} \rangle. \quad (23)$$

The second applicability criteria is the absence of new Fabry-Perot resonances of the stacked system that could arise in matrices $\mathbb{D}_{1,2}$ from equations (5). Thus we require that in the approximation energy range:

$$\det(\mathbb{I} - \tilde{S}_{ud}^b \tilde{S}_{du}^a) \neq 0. \quad (24)$$

III. NUMERICAL EXAMPLE

For the numerical verification of the described approach we conducted a series of optical spectra calculations for the structure that is sketched in Fig. 1. Subsystem A consists of the 150-nm thick homogeneous crystalline Si layer and a 150-nm thick 1D periodic layer of SiO₂ strips embedded into the crystalline Si medium. The period of the structure is 300 nm and the wires are 150-nm wide. The structure is periodic along the x axis and homogeneous along the y axis. The vertical axis z is directed downwards. Structure B is inverted structure A (the periodic layer on the top and the homogeneous on the bottom) with the only difference that the SiO₂ strips width is 160 nm. These two subsystems are surrounded by air, the distance between them are chosen to be zero in order to provide maximum interaction of the coupled resonances. All following calculations are conducted using the Fourier modal method with 23 Fourier harmonics along the periodicity axis for plane electromagnetic waves at normal incidence. Hereinafter, we use the convention that electromagnetic waves with the electric field directed along the y axis are called s-polarized waves.

Using the standard pole-search procedure [17] we obtain two resonances for each subsystem $\omega_{1,2}^a = 1309.43 - 1.47i$, $1326.70 - 6.78i$, $\omega_{1,2}^b = 1316.02 - 1.49i$, $1326.93 - 6.88i$ in the energy range $E = [1.30, 1.35]$ eV. To derive the resonant energies of the stacked system in dependence on the lateral shift along the x axis we substitute




FIG. 1. Schematic of two unit cells of the model structure. Red color denotes the crystalline silicon, blue color denotes SiO₂. Lower subsystem B is 90-nm shifted relative to upper system A. All the layers are 150-nm thick, widths of the upper and lower periodic SiO₂ wires are 150 nm and 160 nm correspondingly.

the calculated resonant data into equation (7) with the proper shift operator (18). One can compare the results obtained directly using the pole-search procedure for the scattering matrix of the whole system and the resonant energies calculated in the resonant mode coupling approximation (Fig. 2 (a)).

Comparison of the FMM-calculated optical spectra and those derived in the resonant mode coupling approximation (16) is presented in Fig. 2 (b). Structure B is chosen to be 90-nm shifted relative to structure A, exactly as depicted in Fig. 1. The four calculated resonances of the stacked system allow us to reproduce the reflection spectrum with proper accuracy. The background matrices are taken as constant and calculated at $\omega_{bg} = 1325$ meV, thus at ω_{bg} the exact scattering matrix of the stacked system is equal to the approximate one.

In order to provide a more comprehensive demonstration of the method's applicability, we have calculated the reflection spectra for the structures with 40 shift values ranging from $d_x = 0$ to $d_x = p$. Results of the exact FMM calculation and the resonant mode coupling approximation calculation are presented in Fig. 3. The maximum difference between the exact and approximate reflection coefficients is 0.195. We consider this accuracy to be good enough for the reproduction of the main features of nanostructures' optical properties. Moreover, we observed more than 200-fold calculation acceleration for the structure of interest with the aforementioned compu-




FIG. 2. Panels (a,b): the real and imaginary parts of resonant energies of the stacked system calculated using the standard pole-search procedure (solid black line) and using the resonant mode coupling approximation (colored lines with diamonds). Panel (c): the norm of the exact scattering matrix (blue solid line), the scattering matrix in the resonant mode coupling approximation (red crosses), and the norm of their difference (magenta dashed line). Panel (d): reflection spectra in s-polarization calculated exactly using the FMM (blue solid line) and using the resonant mode coupling approximation on the bottom (red crosses). Black lines denote the real part of the resonant energies. The calculations are conducted for the 90-nm shift of subsystem B along the x axis (see Fig. 1).




FIG. 3. The reflection spectra of s-polarized plane waves in dependence on the lateral shift of the structure B along the x axis calculated using a) the FMM and b) the resonant mode coupling approximation.

tation parameters: the calculation time of the data presented in Fig.3 with the exact method is 105 seconds vs. 0.5 seconds with the resonant mode coupling method provided that the resonances of the subsystems are known.

IV. CONCLUSION

In conclusion, we proposed a further development of the resonant mode coupling approximation method. We consistently derived the input and output resonant vec-

tors of the stacked system, upper and lower parts of which exhibit distinctive resonances. We showed that the new approximation is capable to reproduce the exact calculation results with reasonable precision. At the same time, the proposed method dramatically decreases the computational time and opens new possibilities for using resonances of nanostructures not only in the analysis of optical spectra but also as a powerful calculation tool. For example, one can prepare a database of optical resonances in simple photonic structures and use the resonant mode coupling method to calculate optical spectra of stacked systems. This calculation procedure could be used in machine learning and genetic algorithms in order

to find the best structure design for enhancement of a selected optical property. Since each resonance is described by two resonant vectors and its complex energy, the developed approach can be implemented even on personal computers.

ACKNOWLEDGMENTS

This work is funded by the Russian Foundation for Basic Research (Grant No. 18-29-20032).

-
- [1] K. Yee, Numerical solution of initial boundary value problems involving Maxwell's equations in isotropic media, *IEEE Transactions on Antennas and Propagation* **14**, 302 (1966).
 - [2] B. T. Draine and P. J. Flatau, Discrete-dipole approximation for scattering calculations, *J. Opt. Soc. Am. A* **11**, 1491 (1994).
 - [3] H. Friedrich and D. Wintgen, Interfering resonances and bound states in the continuum, *Physical Review A* **32**, 3231 (1985).
 - [4] J. Petschulat, C. Menzel, A. Chipouline, C. Rockstuhl, A. Tünnermann, F. Lederer, and T. Pertsch, Multipole approach to metamaterials, *Phys. Rev. A* **78**, 043811 (2008).
 - [5] N. Liu, H. Liu, S. Zhu, and H. Giessen, Stereometamaterials, *Nature Photonics* **3**, 157 (2009).
 - [6] M. F. Limonov, M. V. Rybin, A. N. Poddubny, and Y. S. Kivshar, Fano resonances in photonics, *Nature Photonics* **11**, 543 (2017).
 - [7] A. A. Bogdanov, K. L. Koshelev, P. V. Kapitanova, M. V. Rybin, S. A. Gladyshev, Z. F. Sadrieva, K. B. Samusev, Y. S. Kivshar, and M. F. Limonov, Bound states in the continuum and Fano resonances in the strong mode coupling regime, *Advanced Photonics* **1**, 016001 (2019).
 - [8] N. A. Gippius, T. Weiss, S. G. Tikhodeev, and H. Giessen, Resonant mode coupling of optical resonances in stacked nanostructures, *Opt. Express* **18**, 7569 (2010).
 - [9] T. Weiss, N. A. Gippius, G. Granet, S. G. Tikhodeev, R. Taubert, L. Fu, H. Schweizer, and H. Giessen, Strong resonant mode coupling of Fabry-Perot and grating resonances in stacked two-layer systems, *Photonics and Nanostructures - Fundamentals and Applications* **9**, 390 (2011).
 - [10] S. G. Tikhodeev, A. L. Yablonskii, E. A. Muljarov, N. A. Gippius, and T. Ishihara, Quasiguide modes and optical properties of photonic crystal slabs, *Phys. Rev. B* **66**, 045102 (2002).
 - [11] T. Weiss, M. Schäferling, H. Giessen, N. A. Gippius, S. G. Tikhodeev, W. Langbein, and E. A. Muljarov, Analytical normalization of resonant states in photonic crystal slabs and periodic arrays of nanoantennas at oblique incidence, *Phys. Rev. B* **96**, 045129 (2017).
 - [12] D. A. Bykov and L. L. Doskolovich, Numerical methods for calculating poles of the scattering matrix with applications in grating theory, *J. Lightwave Technol.* **31**, 793 (2013).
 - [13] P. Lalanne, W. Yan, A. Gras, C. Sauvan, J.-P. Hugonin, M. Besbes, G. Demésy, M. D. Truong, B. Gralak, F. Zolla, A. Nicolet, F. Binkowski, L. Zschiedrich, S. Burger, J. Zimmerling, R. Remis, P. Urbach, H. T. Liu, and T. Weiss, Quasinormal mode solvers for resonators with dispersive materials, *J. Opt. Soc. Am. A* **36**, 686 (2019).
 - [14] D. M. Whittaker and I. S. Culshaw, Scattering-matrix treatment of patterned multilayer photonic structures, *Physical Review B* **60**, 2610 (1999).
 - [15] M. Moharam, E. B. Grann, D. A. Pommet, and T. Gaylord, Formulation for stable and efficient implementation of the rigorous coupled-wave analysis of binary gratings, *JOSA A* **12**, 1068 (1995).
 - [16] P. T. Kristensen, K. Herrmann, F. Intravaia, and K. Busch, Modeling electromagnetic resonators using quasinormal modes, *Adv. Opt. Photon.* **12**, 612 (2020).
 - [17] N. A. Gippius, S. G. Tikhodeev, and T. Ishihara, Optical properties of photonic crystal slabs with an asymmetrical unit cell, *Phys. Rev. B* **72**, 045138 (2005).
 - [18] E. A. Muljarov, W. Langbein, and R. Zimmermann, Brillouin-Wigner perturbation theory in open electromagnetic systems, *EPL* **92**, 50010 (2010).